

SUBSTITUTE SPECIFICATION

METHOD FOR REPRODUCING DIRECT CURRENTS, AND A DIRECT
 CURRENT TRANSFORMER FOR CARRYING OUT THE METHOD

#1
 D. M. M. M.
 9/12/01
 Sub Spec

[0001] This application is the national phase under 35 U.S.C. § 371 of PCT International Application No. PCT/DE99/03088 which has an International filing date of September 22, 1999, which designated the United States of America.

Field of the Invention

[0002] The invention relates to a method for reproducing direct currents, in particular for use in DC switchgear, with the aid of a primary winding through which the direct current to be measured flows and which is magnetically coupled to a secondary winding via an iron core. It further relates to a direct current transformer which is suitable for carrying out the method.

Background of the Invention

[0003] The detection of currents in DC circuits is associated with greater technical problems than such detection of currents in AC circuits, in which transmission to a measurement device or to a tripping circuit of a switching device can be carried out using magnetic transformers.

[0004] Furthermore, there is the requirement for low-voltage switchgear for the measurement to be carried out as far as possible from the system, that is to say without providing external energy from an additional energy source which provides an auxiliary voltage. This is also only a minor problem in AC networks, or at least with an energy source having only a low power level.

[0005]

the aid of Hall probes or magnetoresistive sensors. However, it has been found that this method is not very suitable, at least for the preferred situation here, since the primary current cannot be reproduced with sufficient accuracy. As such, spurious tripping of the overcurrent release can thus easily occur.

[0006] It is also known for a measurement resistor (shunt) to be inserted in the primary circuit and for the voltage to be supplied via this measurement resistor to an isolating amplifier, whose output side acts on the tripping circuit. However, this solution is technically highly complex owing to the requirements which the isolating amplifier has to satisfy. Furthermore, there is a continuous, high power loss in the measurement resistor.

[0007] EP-A 0 651 258 discloses a measurement method for direct currents, in which the primary conductor is magnetically coupled to a field winding via an iron core. The latter is energized with a regular, triangular-waveform alternating current, which allows pulses to be produced at regular intervals in a further winding, which is used as a measurement coil. If the iron core is now premagnetized in one direction or the other by means of the primary direct current, then the shift in the hysteresis curve of the iron core changes the interval between the measured pulses, and this can be evaluated as a measure of the primary current to be measured. This solution is likewise very complex in terms of circuitry and requires the continuous provision of an auxiliary voltage with a corresponding power level, thus resulting in a not inconsiderable energy requirement.

[0008] A further method for measuring direct currents is based on the use of a field winding to compensate for a magnetic field caused by the direct current in an

order to control the compensation current in the field winding. The current flowing in the field winding once compensation has been carried out, that is to say once the total field measured by the magnetic field sensor has become zero, is used as a measure of the primary direct current. The method is known, for example, from EP-A 0 294 590 or from DE-A 38 15 100.

[0009] A further option with the aid of magnetic field compensation is described in UK-A 2 029 973. According to this solution, a current in the form of a ramp is fed continuously and repeatedly into the compensation winding, and the magnetic field in the iron core is measured via an indicator winding.

[0010] The compensation method likewise requires a considerable amount of energy to provide a continuous compensation current, and is thus not suitable for the above-mentioned purpose.

SUMMARY OF THE INVENTION

[0011] The invention is based on the object of specifying a measurement method. In one aspect, it involves a direct current transformer, by means of which direct currents can be reproduced as accurately as possible and using considerably less energy.

[0012] According to the invention, the object is achieved by integration of the current signal which is supplied from the secondary winding of an iron core where the current to be measured flows through a primary winding, and by the integrated current value being supplied to a measurement device or to a trigger circuit of a switching device. The integrated current value is preferably adjusted at predetermined time intervals by determining the primary current to be measured with the assistance of a magnetic field sensor, for measuring the magnetic field in the iron

zero by means of a current, in the opposite direction to the primary current, in a compensation winding, and by the integrated current value being corrected to this value.

[0013] The method can expediently be carried out such that the secondary winding is used as the compensation winding for the measurement based on the compensation method.

[0014] The compensation method can advantageously be carried out such that a linear-rising direct current is fed into the secondary winding or into a separate compensation winding.

[0015] The method manages with only a fraction of the energy required by previously known DC/DC converters, since the compensation method is carried out only at time intervals in order to compensate for the drift in the current value determined using the integration method.

[0016] According to the invention, a direct current transformer which is suitable for carrying out the method has a primary winding, through which the primary direct current to be measured flows, and a secondary winding. The windings are magnetically coupled via an iron core. The device further includes a magnetic field sensor for measuring the magnetic field of the iron core and an integration circuit which is connected to the secondary winding, and whose output is connected to a measurement device or to a trigger circuit of a switching device. Finally, a compensation circuit is connected to the secondary winding via a changeover switch, or is connected to a separate compensation winding wound on the iron core. This compensation circuit includes a controllable DC source and an evaluation circuit which processes the current value of the DC source when the magnetic field has been

equal to zero, in order to adjust the integration circuit.

[0017] The magnetic field sensor may be a Hall probe, a magnetoresistive sensor or an indicator winding into which a balanced alternating current is injected and whose voltage imbalance or balance is a measure of the magnetic field in the iron core.

[0018] The iron core is expediently provided with an air gap, in which or in whose vicinity the magnetic field sensor is arranged.

[0019] The secondary winding supplies a signal which corresponds to the di/dt of the primary direct current. The downstream evaluation circuit, preferably based on a microprocessor, integrates the signal from the secondary winding to form the primary direct current. It can then use this value in a known manner to carry out the overcurrent protection.

[0020] Determination of the primary current necessitates long-term integration, in which minor errors over very long times can lead to major discrepancies between the calculated value and the true primary current, so that an overcurrent release would operate unnecessarily. In order to avoid this undesirable long-term effect, the current is measured at certain time intervals with the aid of the magnetic field sensor. For this purpose, a direct current which starts from zero and ramps up linearly with time is fed into the secondary winding or into a separate compensation winding. At the same time, the output signal from the magnetic field sensor is monitored. When a reversal point or a change in polarity occurs in the signal, depending on the type of magnetic field sensor used, then the magnetic field in the air gap is zero. Further, the compensation current, multiplied by the number of turns on the secondary or compensation

value. After this, the current can once again be detected by integration.

[0021] If an indicator winding on the iron core is used for the magnetic field measurement, then a balanced alternating current is injected into this indicator winding. The voltage is measured in parallel with the indicator winding. If the magnetic field is not equal to zero, then the magnetic characteristic of the iron core results in the voltage being imbalanced to a greater or lesser extent. When the magnetic field finally becomes zero as the compensation current rises, then this results in a balanced AC voltage. The sought measurement point has then been reached. In contrast with the compensation method described in relation to the prior art, there is no need to control the compensation current in this case. In fact, the measurement process can be terminated once the linear-rising compensation current has resulted in the magnetic field in the iron core becoming zero.

[0022] The use of such an indicator winding has the advantage over other magnetic field sensors that it is considerably more resistant to temperature. The temperature resistance depends only on the insulation class of the winding. Overtemperatures up to 200°C may be acceptable, with appropriate insulation.

BRIEF DESCRIPTION OF THE DRAWINGS

[0023] The invention will be explained in more detail in the following text with reference to an exemplary embodiment. In the associated drawings:

Figure 1 shows an outline illustration of the arrangement required for the direct current transformer,

Figure 2 shows the signal produced during regular trimming with various magnetic field